

## NM27LV020 2,097,152-Bit (256k x 8) Low Voltage EPROM

### General Description

The NM27LV020 is a high performance Low Voltage Electrical Programmable Read Only Memory. It is manufactured using National's latest  $0.8\mu$  CMOS split gate AMGT<sup>™</sup> EPROM technology. This technology allows the part to operate at speeds as fast as 150 ns over industrial temperatures ( $-40^{\circ}\text{C}$  to  $+85^{\circ}\text{C}$ ).


This Low Voltage and Low Power EPROM is designed with power sensitive hand held and portable battery products in mind. This allows for code storage of firmware for applications like notebook computers, palm top computers, cellular phones, and HDD.

Small outline packages are just as critical to portable applications as Low Voltage and Low Power. National Semiconductor has foreseen this need and provides windowed LCC for prototyping and software development, PLCC for production runs, and TSOP for PC board sensitive users. The NM27LV020 is one member of National's growing Low Voltage product family.

### Features

- 3.0V to 3.6V operation
- 150 ns access time
- Low current operation (Typical)
  - 10 mA  $I_{CC}$  Active Current @ 5 MHz
  - 10  $\mu\text{A}$   $I_{CC}$  Standby Current @ 5 MHz
- Ultra low power operation (Typical)
  - 33  $\mu\text{W}$  Standby Power @ 3.3V
  - 33 mW Active Power @ 3.3V
- Surface mount package options
  - 32-pin TSOP
  - 32-pin PLCC


### Block Diagram



TL/D/12329-1

## Connection Diagrams

PLCC and CLCC Pin Configuration



Top View

TL/D/12329-2


Commercial Temperature Range (0°C to +70°C)  
 $V_{CC} = 3.3 \pm 0.3$

Parameter/Order Number	Access Time (ns)
NM27LV020 C, V, T 150	150
NM27LV020 C, V, T 200	200
NM27LV020 C, V, T 250	250

Pin Names

A0-A17	Addresses
$\overline{CE}$	Chip Enable
$\overline{OE}$	Output Enable
O0-O7	Outputs
PGM	Program
XX	Don't Care (During Read)
Vpp	Programming Voltage

TSOP Pin Configuration



Top View

TL/D/12329-3

Industrial Temperature Range (-40°C to +85°C)  
 $V_{CC} = 3.3 \pm 0.3$

Parameter/Order Number	Access Time (ns)
NM27LV020 CE, VE, TE 150	150
NM27LV020 CE, VE, TE 200	200
NM27LV020 CE, VE, TE 250	250

Package Types: NM27LV020 C, V, T

C = Quartz-Windowed LCC Package

V = PLCC Package

T = TSOP Package

- All packages conform to JEDEC standard
- All versions are guaranteed to function at slower speeds
- Consult your National Semiconductor sales office for new released products and packages.
- Consult your National Semiconductor representative for custom products for your specific application.

## Absolute Maximum Ratings (Note 1)

If Military/Aerospace specified devices are required, please contact the National Semiconductor Sales Office/Distributors for availability and specifications.

Storage Temperature  $-65^{\circ}\text{C}$  to  $+150^{\circ}\text{C}$

All Input Voltage except A9  
with Respect to Ground  $-0.6\text{V}$  to  $+7\text{V}$

$V_{PP}$  and A9 with Respect to Ground  $-0.7\text{V}$  to  $+14\text{V}$

$V_{CC}$  Supply Voltage  
with Respect to Ground  $-0.6\text{V}$  to  $+7\text{V}$

ESD Protection  $>2000\text{V}$

All Output Voltages with  
Respect to Ground (Note 10)  $V_{CC} + 1.0\text{V}$   
 $\text{to GND } -0.6\text{V}$

## Operating Range

Range	Temperature	$V_{CC}$	Tolerance
Commercial	$0^{\circ}\text{C}$ to $+70^{\circ}\text{C}$	3.3V	$\pm 0.3\text{V}$
Industrial	$-40^{\circ}\text{C}$ to $+85^{\circ}\text{C}$	3.3V	$\pm 0.3\text{V}$

## DC Read Characteristics (Over Operating range with $V_{PP} = V_{CC}$ )

Symbol	Parameter	Test Conditions	Min.	Max.	Units
$V_{IL}$	Input Low Level		$-0.3$	0.7	V
$V_{IH}$	Input High Level		2.0	$V_{CC} + 0.3$	V
$V_{OL1}$	Output Low Voltage (TTL)	$I_{OL} = 2.1\text{ mA}$		0.4	V
$V_{OH1}$	Output High Voltage (TTL)	$I_{OH} = -400\text{ mA}$	2.4		V
$V_{OL2}$	Output Low Voltage	$I_{OL} = 100\text{ }\mu\text{A}$		0.2	V
$V_{OH2}$	Output High Voltage (CMOS)	$I_{OH} = 100\text{ }\mu\text{A}$	$V_{CC} - 0.3$		
$I_{SB1}$	$V_{CC}$ Standby Current (CMOS)	$\overline{CE} = V_{CC} \pm 0.3\text{V}$		50	$\mu\text{A}$
$I_{SB2}$	$V_{CC}$ Standby Current (TTL)	$\overline{CE} = V_{IH}$		1	mA
$I_{CC}$	$V_{CC}$ Active Current	$\overline{CE} = \overline{OE} = V_{IL}$ $I/O = 0\text{ }\mu\text{A}$	$f = 5\text{ MHz}$	15	mA
$I_{PP}$	$V_{PP}$ Supply Current	$V_{PP} = V_{CC}$		10	$\mu\text{A}$
$I_{LI}$	Input Load Current	$V_{IN} = 3.6\text{V}$ or GND		1	$\mu\text{A}$
$I_{LO}$	Output Leakage Current	$V_{OUT} = 3.6\text{V}$ or GND	$-10$	10	$\mu\text{A}$

## AC Read Characteristics (Over operating range with $V_{PP} = V_{CC}$ )

Symbol	Parameter	150		200		250		Units
		Min	Max	Min	Max	Min	Max	
$t_{ACC}$	Address to Output Delay		150		200		250	ns
$t_{CE}$	$\overline{CE}$ to Output Delay		150		200		250	ns
$t_{OE}$	$\overline{OE}$ to Output Delay		65		70		75	ns
$t_{DF}$ (Note 2)	Output Disable to Output Float		50		50		50	ns
$t_{OH}$ (Note 2)	Output Hold from Addresses, $\overline{CE}$ or $\overline{OE}$ , whichever Occurred First	0		0		0		ns

## Capacitance $T_a = +25^\circ\text{C}$ , $f = 1\text{ MHz}$ (Note 2)

Symbol	Parameter	Conditions	Typ	Max	Units
$C_{IN1}$	Input Capacitance	$V_{IN} = 0\text{V}$	9	15	pF
$C_{OUT}$	Output Capacitance	$V_{OUT} = 0\text{V}$	12	15	pF

## AC Test Conditions

Output Load 1 TTL Gate and  $C_L = 100\text{ pF}$  (Note 8)

Input Rise and Fall Times  $\leq 5\text{ ns}$


Input Pulse Levels 0.45V to 2.4V

Timing Measurement Reference Level

Inputs 0.8V and 2V

Outputs 0.8V and 2V

## AC Waveforms (Notes 6, 7 and 9)



TL/D/12329-4

**Note 1:** Stresses above those listed under "Absolute Maximum Ratings" may cause permanent damage to the device. This is a stress rating only, and functional operation of the device at these or any other conditions above those indicated in the operational sections of the specification is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

**Note 2:** This parameter is only sampled and is not 100% tested.

**Note 3:**  $\overline{OE}$  may be delayed up to  $t_{ACC} - t_{OE}$  after the falling edge of  $\overline{CE}$  without impacting  $t_{ACC}$ .

**Note 4:** The  $t_{DF}$  and  $t_{CF}$  compare level is determined as follows: High to TRI-STATE®, the measured  $V_{OH1}(DC) - 0.10\text{V}$ ; Low to TRI-STATE, the measured  $V_{OL1}(DC) + 0.10\text{V}$ .

**Note 5:** TRI-STATE may be attained using  $\overline{OE}$  or  $\overline{CE}$ .

**Note 6:** The power switching characteristics of EPROMs require careful device decoupling. It is recommended that at least a  $0.1\text{ }\mu\text{F}$  ceramic capacitor be used on every device between  $V_{CC}$  and GND.

**Note 7:** The outputs must be restricted to  $V_{CC} + 1.0\text{V}$  to avoid latch-up and device damage.

**Note 8:** 1 TTL Gate:  $I_{OL} = 1.6\text{ mA}$ ,  $I_{OH} = -400\text{ }\mu\text{A}$ .  $C_L$ : 100 pF includes fixture capacitance.

**Note 9:**  $V_{PP}$  may be connected to  $V_{CC}$  except during programming.

**Note 10:** Inputs and outputs can undershoot to  $-2.0\text{V}$  for 20 ns Max.

## Programming Characteristics (Notes 1, 2, 3, 4, and 5)

Symbol	Parameter	Condition	Min	Typ	Max	Units
$t_{AS}$	Address Setup Time		1			$\mu\text{s}$
$t_{OES}$	$\overline{OE}$ Setup Time		1			$\mu\text{s}$
$t_{CES}$	$\overline{CE}$ Setup Time		1			
$t_{DS}$	Data Setup Time		1			$\mu\text{s}$
$t_{VPS}$	$V_{PP}$ Setup Time		1			
$t_{VCS}$	$V_{CC}$ Setup Time		1			$\mu\text{s}$
$t_{AH}$	Address Hold Time		0			$\mu\text{s}$
$t_{DH}$	Data Hold Time		1			$\mu\text{s}$
$t_{DF}$	Output Enable to Output Float Delay	$\overline{CE}/\text{PGM} = V_{IL}$	0		60	ns
$t_{PW}$	Program Pulse Width		95	100	105	$\mu\text{s}$
$t_{OE}$	Data Valid from $\overline{OE}$	$\overline{CE}/\text{PGM} = V_{IL}$			100	$\mu\text{s}$
$I_{PP}$	$V_{PP}$ Supply Current during Programming Pulse	$\overline{CE}/\text{PGM} = V_{IL}$			20	mA
$I_{CC}$	$V_{CC}$ Supply Current				20	mA
$T_A$	Temperature Ambient		20	25	30	$^{\circ}\text{C}$
$V_{CC}$	Power Supply Voltage		6.0	6.25	6.5	V
$V_{PP}$	Programming Supply Voltage		12.5	12.75	13.0	V
$t_{FR}$	Input Rise, Fall Time		5			ns
$V_{IL}$	Input Low Voltage			0	0.45	V
$V_{IH}$	Input High Voltage		2.4	4.0		V
$t_{IN}$	Input Timing Reference Voltage		0.8		2.0	V
$t_{OUT}$	Output Timing Reference Voltage		0.8		2.0	V

**Note 1:** National's standard product warranty applies only to devices programmed to specifications described herein.


**Note 2:**  $V_{CC}$  must be applied simultaneously or before  $V_{PP}$  and removed simultaneously or after  $V_{PP}$ . The EPROM must not be inserted into or removed from a board with voltage applied to  $V_{PP}$  or  $V_{CC}$ .

**Note 3:** The maximum absolute allowable voltage which may be applied to the  $V_{PP}$  pin during programming is 14V. Care must be taken when switching the  $V_{PP}$  supply to prevent any overshoot from exceeding this 14V maximum specification. At least a 0.1  $\mu\text{F}$  capacitor is required across  $V_{CC}$  to GND to suppress spurious voltage transients which may damage the device.

**Note 4:** Programming and program verify are tested with the fast Program Algorithm at typical power supply voltages and timings.

**Note 5:** During power up the PGM pin must be brought high ( $V_{IH}$ ) either coincident with or before power is applied to  $V_{PP}$ .

## Programming Waveform (Note 3)



TL/D/12329-5

# Fast Programming Algorithm Flow Chart




FIGURE 1

TL/D/12329-6



## Functional Description

### DEVICE OPERATION

The six modes of operation of the EPROM are listed in Table I. It should be noted that all inputs for the six modes are at TTL levels. The power supplies required are  $V_{CC}$  and  $V_{PP}$ . The  $V_{PP}$  power supply must be at 12.75V during the three programming modes, and must be at 3.3V in the other three modes. The  $V_{CC}$  power must be at 6.25V during the three programming modes, and at 3.3V in the other three modes.

#### Read Mode

The EPROM has two control functions, both of which must be logically active in order to obtain data at the outputs. Chip Enable ( $\overline{CE}$ ) is the power control and should be used for device selection. Output Enable ( $\overline{OE}$ ) is the output control and should be used to gate data to the output pins, independent of device selection. Assuming that addresses are stable, address access time ( $t_{ACC}$ ) is equal to the delay from  $\overline{CE}$  to output ( $t_{CE}$ ). Data is available at the outputs  $t_{OE}$  after the falling edge of  $\overline{OE}$ , assuming that  $\overline{CE}$  has been low and addresses have been stable for at least  $t_{ACC} - t_{OE}$ .

#### Standby Mode

The EPROM has a standby mode which reduces the active power dissipation by over 99%, from 33 mW to 33  $\mu$ W. The EPROM is placed in the standby mode by applying a CMOS high signal to the  $\overline{CE}$  input. When in standby mode, the outputs are in a high impedance state, independent of the  $\overline{OE}$  input.

#### Output Disable

The EPROM is placed in output disable by applying a TTL high signal to the  $\overline{OE}$  input. When in output disable all circuitry is enabled, except the outputs are in a high impedance state (TRI-STATE).

#### Output OR-Tying

Because the EPROM is usually used in larger memory arrays, National has provided a 2-line control function that accommodates this use of multiple memory connections. The 2-line control function allows for:

- the lowest possible memory power dissipation, and
- complete assurance that output bus contention will not occur.

To most efficiently use these two control lines, it is recommended that  $\overline{CE}$  be decoded and used as the primary device selecting function, while  $\overline{OE}$  be made a common connection to all devices in the array and connected to the READ line from the system control bus. This assures that all selected memory devices are in their low power standby modes and that the output pins are active only when data is desired from a particular memory device.

#### Programming

**CAUTION:** Exceeding 14V on pin 22 ( $V_{PP}$ ) will damage the EPROM.

Initially, and after each erasure, all bits of the EPROM are in the "1's" state. Data is introduced by selectively programming "0's" into the desired bit locations. Although only "0's" will be programmed, both "1's" and "0's" can be presented in the data word. The only way to change a "0" to a "1" is by ultraviolet light erasure.

The EPROM is in the programming mode when the  $V_{PP}$  power supply is at 12.75V and  $\overline{OE}$  is at  $V_{IH}$ . It is required that at least a 0.1  $\mu$ F capacitor be placed across  $V_{CC}$  to ground to suppress spurious voltage transients which may damage the device. The data to be programmed is applied 8 bits in parallel to the data output pins. The levels required for the address and data inputs are TTL.

When the address and data are stable, an active low, TTL program pulse is applied to the  $\overline{PGM}$  input. A program pulse must be applied at each address location to be programmed. The EPROM is programmed with the Fast Programming Algorithm shown in Figure I. Each Address is programmed with a series of 100  $\mu$ s pulses until it verifies good, up to a maximum of 25 pulses. Most memory cells will program with a single 100  $\mu$ s pulse.

The EPROM must not be programmed with a DC signal applied to the  $\overline{PGM}$  input.

Programming multiple EPROM in parallel with the same data can be easily accomplished due to the simplicity of the programming requirements. Like inputs of the parallel EPROM must be connected together when they are programmed with the same data. A low level TTL pulse applied to the  $\overline{PGM}$  input programs the paralleled EPROM.

#### Program Inhibit

Programming multiple EPROM's in parallel with different data is also easily accomplished. Except for  $\overline{CE}$  all like inputs (including  $\overline{OE}$  and  $\overline{PGM}$ ) of the parallel EPROM may be common. A TTL low level program pulse applied to an EPROM's  $\overline{PGM}$  input with  $\overline{CE}$  at  $V_{IL}$  and  $V_{PP}$  at 12.75V will program the EPROM. A TTL high level  $\overline{CE}$  input inhibits the other EPROMs from being programmed.

#### Program Verify

A verify should be performed on the programmed bits to determine whether they were correctly programmed. The verify may be performed with  $V_{PP}$  at 6.25V.  $V_{PP}$  must be at  $V_{CC}$  except during programming and program verify.

#### AFTER PROGRAMMING

Opaque labels should be placed over the EPROM window to prevent unintentional erasure. Covering the window will also prevent temporary functional failure due to the generation of photo currents.


#### MANUFACTURER'S IDENTIFICATION CODE

The EPROM has a manufacturer's identification code to aid in programming. When the device is inserted in an EPROM programmer socket, the programmer reads the code and then automatically calls up the specific programming algorithm for the part. This automatic programming control is only possible with programmers which have the capability of reading the code. The Manufacturers Identification code, shown in Table II, specifically identifies the manufacture and device type. The code for NM27LV020 is '8F07', where '8F' designates that it is made by National Semiconductor, and '07' designates a 2 Megabit (256K x 8) part.

The code is accessed by applying 12V  $\pm 0.5$ V to address pin A9. Addresses A1-A8, A10-A16, and all control pins are held at  $V_{IL}$ . Address pin A0 is held at  $V_{IL}$  for the manufacturer's code, and held at  $V_{IH}$  for the device code. The code is read on the eight data pins, O0-O7. Proper code access is only guaranteed at 25°C  $\pm 5^\circ$ C.

# Physical Dimensions inches (millimeters) (Continued)

Lit # 112261-002



**32-Lead PLCC Package (V)**  
**Order Number NM27LV020VXXX**  
**NS Package Number VA32A**

## LIFE SUPPORT POLICY

NATIONAL'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT OF NATIONAL SEMICONDUCTOR CORPORATION. As used herein:

- Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and whose failure to perform, when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury to the user.
- A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.



**National Semiconductor Corporation**  
2900 Semiconductor Drive  
P.O. Box 58090  
Santa Clara, CA 95052-8090  
Tel: (1800) 272-9959  
TWX: (910) 339-9240

**National Semiconductor GmbH**  
Industriestrasse 10  
D-82256 Fürstfeldbruck  
Germany  
Tel: (0-81-41) 103-0  
Telex: 527649  
Fax: (0-81-41) 10-35-06

**National Semiconductor Japan Ltd.**  
Sumitomo Chemical  
Engineering Center  
Bldg. 7F  
1-7-1, Nakase, Mihama-Ku  
Chiba-City,  
Chiba Prefecture 261  
Tel: (043) 299-2300  
Fax: (043) 299-2500

**National Semiconductor Hong Kong Ltd.**  
13th Floor, Straight Block  
Ocean Centre, 5 Canton Rd.  
Tsimshatsui, Kowloon  
Hong Kong  
Tel: (852) 737-1600  
Telex: 51292 NSHKL  
Fax: (852) 736-9990

**National Semiconductores Do Brazil Ltda.**  
Rue Deputado Lacorda Franco  
120-3A  
Sao Paulo-SP  
Brazil 05418-000  
Tel: (55-11) 212-5066  
Telex: 391-1131931 NSBR BR  
Fax: (55-11) 212-1181

**National Semiconductor (Australia) Pty. Ltd.**  
16 Business Park Dr.  
Notting Hill, VIC 3168  
Australia  
Tel: (3) 558-9999  
Fax: (3) 558-9998



## ERASURE CHARACTERISTICS

The erasure characteristics of the device are such that erasure begins to occur when exposed to light with wavelengths shorter than approximately 4000 Angstroms (Å). It should be noted that sunlight and certain types of fluorescent lamps have wavelengths in the 3000Å–4000Å range.

The recommended erasure procedure for the EPROM is exposure to short wave ultraviolet light which has a wavelength of 2537Å. The integrated dose (i.e., UV intensity x exposure time) for erasure should be a minimum of 30 Wsec/cm<sup>2</sup>.

The EPROM should be placed within one inch of the lamp tubes during erasure. Some lamps have a filter on their tubes which should be removed before erasure.

An erasure system should be calibrated periodically. The distance from lamp to device should be maintained at one inch. The erasure time increases as the square of the distance from the lamp (if distance is doubled the erasure time increases by factor of four). Lamps lose intensity as they age. When a lamp is changed, the distance has changed, or the lamp has aged, the system should be checked to make certain full erasure is occurring. Incomplete erasure will

cause symptoms that can be misleading. Programmers, components, and even system designs have been erroneously suspected when incomplete erasure was the problem.

## SYSTEM CONSIDERATION

The power switching characteristics of EPROMs require careful decoupling of the devices. The supply current,  $I_{CC}$ , has three segments that are of interest to the system designer: the standby current level, the active current level, and the transient current peaks that are produced by voltage transitions on input pins. The magnitude of these transient current peaks is dependent on the output capacitance loading of the device. The associated  $V_{CC}$  transient voltage peaks can be suppressed by properly selected decoupling capacitors. It is recommended that at least a 0.1  $\mu$ F ceramic capacitor be used on every device between  $V_{CC}$  and GND. This should be a high frequency capacitor of low inherent inductance. In addition, at least a 4.7  $\mu$ F bulk electrolytic capacitor should be used between  $V_{CC}$  and GND for each eight devices. The bulk capacitor should be located near where the power supply is connected to the array. The purpose of the bulk capacitor is to overcome the voltage drop caused by the inductive effects of the PC board traces.

## Mode Selection

The modes of operation of the NM27LV020 are listed in Table I. A single 3.3V power supply is required in the read mode. All inputs are TTL levels except for  $V_{PP}$  and A9 for device signature.

Table I. Modes Selection


Mode	Pins	$\overline{CE}$	$\overline{OE}$	PGM	$V_{PP}$	$V_{CC}$	Outputs
Read		$V_{IL}$	$V_{IL}$	X	$V_{CC}$	3.3V	$D_{OUT}$
Output Disable		X (Note 1)	$V_{IH}$	X	$V_{CC}$	3.3V	High Z
Standby		$V_{IH}$	X	X	$V_{CC}$	3.3V	High Z
Programming		$V_{IL}$	$V_{IH}$	$V_{IL}$	12.75V	6.25V	$D_{IN}$
Program Verify		$V_{IL}$	$V_{IL}$	$V_{IH}$	12.75V	12.75V	$D_{OUT}$
Program Inhibit		$V_{IH}$	$V_{IH}$	X	12.75V	6.25V	High Z

Note: X can be  $V_{IL}$  or  $V_{IH}$

Table II. Manufacturer's Identification Code

Mode	Pins	A0 (12)	A9 (26)	O7 (21)	O6 (20)	O5 (19)	O4 (18)	O3 (17)	O2 (15)	O1 (14)	O0 (13)	Hex Data
Manufacturer Code		$V_{IL}$	12V	1	0	0	0	1	1	1	1	8F
Device Code		$V_{IH}$	12V	0	0	0	0	0	1	1	0	07

# Physical Dimensions inches (millimeters)



**32-Lead TSOP Package (T)**  
**Order Number NM27LV020TXXX**  
**NS Package Number MBH32A**